



100W Single Output Switching Power Supply

RS-100 series



Features:

Universal AC input / Full range

Protections: Short circuit / Overload / Over voltage

Cooling by free air convection LED indicator for power on 100% full load burn-in test

All using 105 long life electrolytic capacitors

Withstand 300VAC surge input for 5 second High operating temperature up to 70

Withstand 5G vibration test

High efficiency, long life and high reliability

3 years warranty





CBCE

SPECIFICATION

| MODEL | | RS-100-3.3 | RS-100-5 | RS-100-12 | RS-100-15 | RS-100-24 | RS-100-48 |
|-----------------------------|--|---|-----------------------|------------------------|-------------------------|--------------|--------------|
| ОИТРИТ | DC VOLTAGE | 3.3V | 5V | 12V | 15V | 24V | 48V |
| | RATED CURRENT | 20A | 16A | 8.5A | 7A | 4.5A | 2.3A |
| | CURRENT RANGE | 0 ~ 20A | 0 ~ 16A | 0 ~ 8.5A | 0 ~ 7A | 0 ~ 4.5A | 0 ~ 2.3A |
| | RATED POWER | 66W | 80W | 102W | 105W | 108W | 110.4W |
| | RIPPLE & NOISE (max.) Note.2 | 80mVp-p | 80mVp-p | 120mVp-p | 120mVp-p | 120mVp-p | 200mVp-p |
| | VOLTAGEADJ. RANGE | 3.2V ~ 3.5V | 4.75 ~ 5.5V | 11.4 ~ 13.2V | 14.25 ~ 16.5V | 22.8 ~ 26.4V | 45.6 ~ 52.8V |
| | VOLTAGETOLERANCE Note.3 | ± 3.0% | ± 2.0% | ± 1.0% | ± 1.0% | ± 1.0% | ± 1.0% |
| | LINE REGULATION Note.4 | ± 0.5% | ± 0.5% | ± 0.5% | ± 0.5% | ± 0.5% | ± 0.5% |
| | LOAD REGULATION Note.5 | ± 2.0% | ± 1.0% | ± 0.5% | ± 0.5% | ± 0.5% | ± 0.5% |
| | SETUP, RISETIME | 500ms, 20ms/230VAC 1200ms, 30ms/115VAC at full load | | | | | |
| | HOLD UP TIME (Typ.) | 100ms/230VAC 18ms/115VAC at full load | | | | | |
| INPUT | VOLTAGERANGE | 88 ~ 264VAC 125~ 373VDC (Withstand 300VAC surge for 5sec. Without damage) | | | | | |
| | FREQUENCY RANGE | 47 ~ 63Hz | | | | | |
| | EFFICIENCY (Typ.) | 74% | 77% | 81% | 82% | 84% | 84% |
| | AC CURRENT (Typ.) | 2.5A/115VAC 1.5A/230VAC | | | | | |
| | INRUSH CURRENT (Typ.) | COLD START 40A/230VAC | | | | | |
| | LEAKAGE CURRENT | <2mA / 240VAC | | | | | |
| PROTECTION | | 110 ~ 150% ratedoutput power | | | | | |
| | OVERLOAD | Protection type: Hiccup mode, recovers automatically after fault condition is removed | | | | | |
| | OVER VOLTAGE | 3.8 ~ 4.45V | 5.75 ~ 6.75V | 13.8 ~ 16.2V | 17.25 ~ 20.25V | 27.6 ~ 32.4V | 55.2 ~ 64.8V |
| | | Protection type : His | ccup mode, recovers a | utomatically after fau | It condition is removed | | |
| ENVIRONMENT | WORKING TEMP. | -25 ~ +70 (Refer to "Derating Curve") | | | | | |
| | WORKING HUMIDITY | 20 ~ 90% RH non-condensing | | | | | |
| | STORAGE TEMP., HUMIDITY | -40 ~ +85 , 10 ~ 95% RH | | | | | |
| | TEMP. COEFFICIENT | ±0.03%/ (0~50) | | | | | |
| | VIBRATION | 10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes | | | | | |
| SAFETY & EMC (Note 6) | SAFETY STANDARDS | UL60950-1, TUV EN60950-1 approved | | | | | |
| | WITHSTAND VOLTAGE | I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC | | | | | |
| | ISOLATION RESISTANCE | I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25J/ 70% RH | | | | | |
| | EMC EMISSION | Compliance to EN55022 (CISPR22) Class B, EN61000-3-2,-3 | | | | | |
| | EMC IMMUNITY | Compliance to EN61000-4-2,3,4,5,6,8,11, EN61000-6-2 (EN50082-2), heavy industry level, criteria A | | | | | |
| OTHERS | MTBF | 260.8Khrs min. MIL-HDBK-217F (25) | | | | | |
| | DIMENSION | 159*97*38mm (L*W*H) | | | | | |
| | PACKING | 0.6Kg; 24pcs/15.4K | g/0.7CUFT | | | | |
| NOTE | All parameters NOT special Ripple & noise are measure Tolerance: includes set up Line regulation is measured Load regulation is measured The power supply is conside | ly mentioned are measured at 230VAC input, rated load and 25 of ambient temperature. If you mentioned are measured at 230VAC input, rated load and 25 of ambient temperature. If you have a composition and load regulation. If no low line to high line at rated load. If of 100% rated load. If of 100% rated load. If of 100% rated load. If you have a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets not now to perform these EMC tests, please refer to "EMI testing of component power supplies." | | | | | |

7. Length of set up time is measured at cold first start. Turning ON/OFF the power supply very quickly may lead to increase of the set up time.





100W Single Output Switching Power Supply

RS-100 series

